

# 河北科技大学试卷

河北科技大学 2005—2006 学年第一学期

## 《化学反应工程》期末考试试卷

学院 \_\_\_\_\_ 班级 \_\_\_\_\_ 姓名 \_\_\_\_\_ 学号 \_\_\_\_\_

题号	一	二	三	四	五	六	总分
得分							

### 一、简答题

- 1、气—液相间的传质模型有哪几种？并加以说明。
- 2、无因次准数  $M$  的物理意义？如何利用  $M$  值判断反应类别？
- 3、简述固定床与流化床的特点，并各举出两个应用实例。
- 4、简述气—固相固定床反应器数学模型的分类及选取原则。结合课程设计说明利用一维数学模型进行反应器设计计算的方法。
- 5、简述在多孔固体催化剂上进行气—固相催化反应的步骤。

### 二、选做题（从下列两题中任选一题）

- 1、写出外扩散有效因子  $\zeta_{ex}$  的一般表达式，并证明：  $n = -1$  时，外扩散有效因子  $\zeta_{ex} = 2/[1 + (1 - 4Da)^{1/2}]$ 。
- 2、对下述反应，  $2A \rightarrow P$ ,  $r_P = k_1 C_A^2$ ;  $A + B \rightarrow R$ ,  $r_R = k_2 C_A C_B$ ;  $2B \rightarrow T$ ,  $r_T = k_3 C_B^2$ ，试证明要使  $R$  的选择性最大，在 CSTR 中，  $A$  与  $B$  浓度之比应为： $C_A/C_B = (k_3/k_1)^{1/2}$ 。

三、有一液相反应  $A \rightarrow P + S$ , 其反应速率  $-r_A = kC_A^2$ ,  $k = 10 \text{ m}^3/\text{Kmol} \cdot \text{hr}$ ,  $C_{A0} = 0.2 \text{ Kmol/m}^3$ ,  $V_0 = 2 \text{ m}^3/\text{hr}$ , 比较下列方案, 何者转化率最大?

- (1) PFR, 体积为  $4 \text{ m}^3$ ; (2) PFR  $\rightarrow$  CSTR, 体积各为  $2 \text{ m}^3$ ;  
(3) CSTR  $\rightarrow$  PFR, 体积各为  $2 \text{ m}^3$ ; (4) CSTR  $\rightarrow$  CSTR, 体积各为  $2 \text{ m}^3$ 。

四、填空:

- 1、反应器的设计放大方法主要有 ( ) ( ) ( ) ( )。
- 2、按照操作方式, 反应器可分为 ( ) ( ) ( ) ( )。
- 3、理想流动模型包括 ( ) ( ) ( )。
- 4、固体催化剂中气体组分的扩散形式主要有 ( ) ( ) ( ) ( ) ( )。
- 5、描述停留时间分布的两个函数是 ( ) ( ) ( )。
- 6、转化率、收率、选择性三者关系为 ( ) ( ) ( )。
- 7、固体催化剂的主要制备方法有 ( ) ( ) ( ) ( ) ( ) ( )。
- 8、气—液反应器按气—液相接触形态可分为 ( ) ( ) ( ) ( ) ( )。
- 9、化学吸收增强因子的物理意义是 ( ) ( )。
- 10、本征动力学与宏观动力学分别是指 ( ) ( ) ( ) ( )。

五、等温下在 BR 中进行一级不可逆液相分解反应  $A \rightarrow B + C$ , 在 10 分钟内有 50% 的 A 分解, 要达到分解率为 80%, 问需要多少时间? 若反应为二级, 则需要多少时间?

六、英文题（学其它语种的同学做下面的中文题）

An aqueous reactant stream passes through a mixed flow reactor followed by a plug flow reactor. The initial concentration of A is 4mol/liter. Find the concentration at the exit of the plug flow reactor if in the mixed flow reactor  $C_A=1\text{mol/liter}$ . The reaction is first-order with respect to A, and the volume of the plug flow unit is three times that of the mixed flow unit.

某二级液相反应，在 PFR 中达到 99% 转化率需反应时间 10 分钟，如在 CSTR 中进行时，需反应时间为多少？

**B 卷 共 (3) 页, 第 (3) 页**